



LED LIGHT STRIP

Details

The LED Light strip provides high quality high quality LED lighting while being low consumption. With the RGB setting you can create over 16.7 million colours to perfectly suit your event. Also can be set to strobe, gradual change, and jump change.

Specifications

- Dimensions: L 3.3' x W 2.5" x H 3.25"
- Weight: 2kg
- Total Wattage: 22 W
- Intensive brightness LEDs: 258 pcs 10mm LEDs
- Beam angle: 25 deg beam angle of each LED
- Power supply: Voltage: 100-240 VAC / Frequency: 50-60 Hz
- Input voltage: AC 100V-264V/50-60HZ
- Control mode: standalone/ master and slaver
- The unit is compatible with the standard DMX 512 signal for external DMX control.

Operating Instructions

Press MENU to select Menu type:

SouF: Voice-activated strobe mode (unsuitable for out-door use)

SouA: Voice-activated no strobe mode (unsuitable for out-door use)

SP: Colour change stobe (Use up/down to adjust speed)

PR: Preset options (Use up/down to select pre-set)

Pr00:red; Pr01:green; Pr02:blue; Pr03:amber; Pr04:white; Pr05:yellow;
Pr06:purple; Pr07-30:Other colours; Pr31-38: Colours+strobe

FA: gradual colour change mode: Transitions through the colour spectrum (Use up/down to adjust speed of fade)

FL: white color strobe (Use up/down to adjust speed of strobe)

To Create your own colour change combination of **RGBAU** settings example:

R: Red (use up/down to adjust amount of red)

G: Green (use up/down to adjust amount of green)

B: Blue (use up and down to adjust amount of blue)

A: Amber (use up and down to adjust amount of amber)

U: White (use up and down to adjust amount of white)

Color	Name	Red	Green	Blue	Amber	White
	Red	255	0	0	0	0
	Green	0	255	0	0	0
	Blue	0	0	255	0	0
	Amber	0	0	0	255	0
	White	0	0	0	0	255
	Yellow	255	255	0	0	0
	Magenta	255	0	255	0	0
	Cyan	0	255	255	0	0
	Champagne	0	0	0	255	255
	Cold White	255	255	255	0	0
	Warm White	255	255	255	255	255